

MODIG S firmware upgrade

Necessary material:

- Modig S
- USB 2.0 memory ;
- New firmware of MODIG S;
- PC;

Previous steps:

- Download last firmware version available for your modulator MODIG S. You can find at: <http://www.ftemaximal.com>
- Unzip the file downloaded from the web site. It contains:
 - dm-01tha.img

Upgrading:

1. Copy the file dm-01tha.img in the root directory of the USB 2.0 memory.
2. Safe extract the USB 2.0 memory from the computer.
3. If the modulator was on please, turn off the modulator.
4. Connect the USB 2.0 memory in the USB port of the modulator MODIG S.
5. Turn on the modulator and wait until the 7 segment display show the settings in sequence.
6. Remove the USB 2.0 disk from the USB port of the modulator.
7. Turn off and turn on the modulator to boot with the new firmware.