



MF 101

Technical specifications. Mast blinded mixer MF 101

		MF 101
Code		9000102
Inputs and bands		3: VHF / UHF / UHF
Frequencies (MHz)	VHF	5 - 300
	UHF	470 - 862
Insertion loss (dB)	VHF	1
	UHF	4,5
Impedance input / output (Ω)		75
Current pass		2 UHF inputs by jumpers
Connectors type		F
Installation type		Mast
Dimensions (W x H x D) (mm)	without box	104,6 x 44 x 24,2
	with box	115 x 110 x 57
Accessories		Outdoors box EQ BOX Cable tie 7mm
Packing quantity		1 / 10 / 60



Jumpers configurations